


  PowerSports Flooded  										
BCI Group Size	Part Number	Brand	Volts	Ah Capacity (10 hr)	CCA	Length (in)	Width (in)	Height (in)	Assembly Figure	UPGRADE TO AGM
Premium Flooded Powersport										
6N6-3B	027-1003	Motomaster	6	6	--	6-5/16	4-5/8	5	G	027-1065
3L-A	027-1024	Motomaster	12	3	30	6-5/16	4-5/8	5	F	
4L-B	027-1007	Motomaster	12	4	45	4-3/4	2-7/8	3-11/16	D	
5L-B	027-1008	Motomaster	12	5	65	7-5/16	5-7/16	5-7/16	D	
7-A	027-1060	Motomaster	12	8	100	6	6	5-7/8	C	
9A-A	027-1056	Motomaster	12	9	115	5-3/8	3	6-1/16	C	
9-B	027-1006	Motomaster	12	9	115	5-3/8	3	5-1/2	E	
10L-A2	027-1015	Motomaster	12	11	160	5-3/8	3-9/16	5-3/4	F	
10L-B	027-1036	Motomaster	12	11	160	7	6-1/8	7	D	
12A-A	027-1018	Motomaster	12	12	165	5-5/16	3-3/16	6-5/16	C	
12AL-A	027-1023	Motomaster	12	12	165	5-5/16	3-3/16	6-5/16	F	
14-A2	027-1000	Motomaster	12	14	175	5-5/16	3-9/16	6-9/16	C	027-1069
14A-A2	027-1022	Motomaster	12	14	175	5-5/16	3-9/16	6-15/16	C	027-1069
14L-A2	027-1016	Motomaster	12	14	175	5-5/16	3-9/16	6-9/16	F	027-1071
14L-B2	027-1055	Motomaster	12	14	175	7	6-1/8	7	D	027-1071
16A-AB	027-1025	Motomaster	12	16	210	5-15/16	3-9/16	7-3/16	C	027-1037
16AL-A2	027-1019	Motomaster	12	16	200	8-1/16	2-7/8	6-7/16	F	
12C-A	027-1064	Motomaster	12	18	150	5-5/16	3-3/16	6-7/8	C	
18-A	027-1027	Motomaster	12	18	235	8-5/8	7-7/16	7-7/16	C	
18L-A	027-1021	Motomaster	12	18	235	8-5/8	7-7/16	7-7/16	F	
HD-12	027-1030	Motomaster	12	18	200	8-1/16	5-1/8	6-1/2	C	027-1088
16-B	027-1020	Motomaster	12	19	240	6-15/16	4	6-1/8	E	
16CL-B	027-1005	Motomaster	12	19	240	6-7/8	4	6-7/8	D	
16L-B	027-1032	Motomaster	12	19	240	6-15/16	4	6-1/8	D	027-1077
50-N18L-A3	027-1033	Motomaster	12	20	240	8-1/8	3-9/16	6-7/16	F	027-1090

Cross Reference Chart	
BCI Group Size	Product Number
12N5-3B	027-1008
16-BS	027-1088
18L-BS	027-1090
CN18L-BS	027-1090

PowerSports AGM (Absorbed Glass Mat)										
BCI Group Size	Part Number	Brand	Volts	Ah Capacity (10 hr)	CCA	Length (in)	Width (in)	Height (in)	Assembly Figure	
Ultra High Performance AGM (Absorbed Glass Mat) Powersport										
4L-BS	027-1065	Motomaster Eliminator	12	3	40	4-7/16	2-3/4	3-3/8	B	
7L-BS	027-1070	Motomaster Eliminator	12	3	95	4-1/2	2-3/4	5	B	
5L-BS	027-1067	Motomaster Eliminator	12	4	60	4-7/16	2-3/4	4-1/8	B	
7A-BS	027-1072	Motomaster Eliminator	12	6	100	5-7/8	3-7/16	3-11/16	A	
7B-BS	027-1096	Motomaster Eliminator	12	6	100	5-7/8	3-7/16	3-11/16	A	
7S-BS	027-1092	Motomaster Eliminator	12	6	100	5-7/8	3-7/16	3-11/16	B	
9-BS	027-1058	Motomaster Eliminator	12	8	135	5-7/8	3-7/16	4-3/16	A	
9B-BS	027-1097	Motomaster Eliminator	12	8	115	5-7/8	3-7/16	4-3/16	A	
10S-BS	027-1093	Motomaster Eliminator	12	10	180	5-7/8	3-7/16	7-9/16	A	
12-BS	027-1028	Motomaster Eliminator	12	10	170	5-7/8	3-7/16	5-3/16	A	
12A-BS	027-1073	Motomaster Eliminator	12	10	150	6-5/8	6-1/16	5-3/4	A	
12B-BS	027-1098	Motomaster Eliminator	12	10	125	6-5/8	6-1/16	5-3/4	A	
12S-BS	027-1094	Motomaster Eliminator	12	10	190	6-5/8	6-1/16	5-3/4	A	
14-BS	027-1029	Motomaster Eliminator	12	12	190	5-7/8	3-7/16	5-3/4	A	
14AH-BS	027-1069	Motomaster Eliminator	12	12	190	5-5/16	3-1/2	6-9/16	A	
14AHL-BS	027-1071	Motomaster Eliminator	12	12	190	5-5/16	3-1/2	6-9/16	B	
14B-BS	027-1099	Motomaster Eliminator	12	12	170	6	3-7/16	5-3/4	A	
14L-BS	027-1085	Motomaster Eliminator	12	12	190	6	3-7/16	5-3/4	B	
14S-BS	027-1095	Motomaster Eliminator	12	12	210	6	3-7/16	5-3/4	A	
15L-BS	027-1086	Motomaster Eliminator	12	13	245	6-7/8	3-7/16	5-1/8	B	
20H-BS	027-1089	Motomaster Eliminator	12	18	310	6-7/8	3-3/8	6-1/16	A	
20CH-BS	027-1088	Motomaster Eliminator	12	18	275	6	3-7/16	6-3/8	A	
20L-BS	027-1037	Motomaster Eliminator	12	18	270	6-15/16	3-7/16	6	B	
16CLB-BS	027-1087	Motomaster Eliminator	12	19	270	6-7/8	4	6-7/8	B	
16L-BS	027-1077	Motomaster Eliminator	12	19	220	6-15/16	4	6-1/8	B	
24HL-BS	027-1090	Motomaster Eliminator	12	21	330	8-1/8	3-7/16	6-3/8	B	
30CLB-BS	027-1091	Motomaster Eliminator	12	30	395	6-1/2	5-1/8	7-9/16	B	
30L-BS	027-1079	Motomaster Eliminator	12	30	395	6-1/2	4-15/16	6-7/8	B	



Product specifications are subject to change.